



BELLE
LIGHT
CONSTRUCTION
EQUIPMENT



Altrad-Belle.com

BCS6 **E+**

82V 6-PORT RAPID CHARGING STATION



The Altrad Belle BCS6 **E+** Rapid Charging Station is designed to charge up to six batteries simultaneously, with 6 x 4A charging slots for maximum efficiency.

Built with integrated battery cooling and clear LED charge status indicators, it ensures safe and reliable charging every time.

The unit is fully compatible with all Altrad Belle **82v** professional batteries up to 8Ah....

...Building a Sustainable Future!



FEATURES & BENEFITS

- Charges 6 x **E+ 82v** 5Ah batteries in 100 minutes.
Charges 6 x **E+ 82v** 8Ah batteries in 130 minutes.
- Batteries no longer need to be swapped between transport boxes and chargers. Once fully charged, the box can be easily carried to any workplace.
- Suitable for both indoor use, the 6-slot charger is equipped with an automatic closing system that keeps batteries protected, ensuring they stay dry even in the rain.
- Fully compatible with all Altrad Belle **E+ 82v** batteries up to 8Ah.
- Self-closing lid to stop rain / water entering the charging ports.
- Fold-away transport handle for each transportation.
- Cable storage hooks eliminates the problem of trailing cables that may be a tripping hazard.



**6 X CHARGING PORTS FOR
MULTI-BATTERY CHARGING**



**FOLD-AWAY TRANSPORT
HANDLE**



CABLE STORAGE HOOKS

TECHNICAL SPECIFICATIONS

Model

Model Code		BCS6 E+
Battery Slots		OPM/21/DIO
IP Rating		6
Input Voltage AC	(V)	IPX4
Input Frequency	(Hz)	220 / 240
Input Current	(A)	50 / 60
Output Voltage	(V)	15 Max.
Output Current	(A)	82
*Weight	(Kg)	8 Max. x 3
		19

5Ah Battery

80% Charge Time - 6 Batteries	(Mins)	56
100% Charge Time - 6 Batteries	(Mins)	100

8Ah Battery

80% Charge Time - 6 Batteries	(Mins)	100
100% Charge Time - 6 Batteries	(Mins)	130

